Groovebox

Sonicware SmplTrek

33 parameters · 5 sections · plain CC, no NRPN · transcribed from the maker's manual

Receive only
The chart marks every one of these as recognized and none as transmitted. SmplTrek listens to them and does not send them.

Channels
The project rows answer on the project channel, the track rows on each track's own.

Project	6	
Project Playback	switch	30
Scene Playback	switch	31
Track Shift		32
Master Level		33
Project Level		34
Prj-Ext Balance		35

Insert FX	6	
On/Off	switch	36
Type		37
Parameter 1		38
Parameter 2		39
Parameter 3		40
Parameter 4		41

Send FX	6	
On/Off	switch	42
Type		43
Parameter 1		44
Parameter 2		45
Parameter 3		46
Parameter 4		47

Master FX	6	
On/Off	switch	48
Type		49
Parameter 1		50
Parameter 2		51
Parameter 3		52
Parameter 4		53

Track	9	
Track Playback	switch	60
Track Level		61
Track Pan		62
Track Send FX		63
Track Mute	switch	64
Track EQ Type		65
Track EQ Freq		66
Track EQ Amount		67
Pitch		68

These controls as knobs on your iPhone or iPad
Sequentia has this chart built in, with a looper for knob movement and tempo-locked LFOs on any CC.

synthycraft.com/l/sequentia