Synth

Arturia MiniFreak

41 parameters · 15 sections · plain CC, no NRPN · transcribed from the maker's manual

Channels
One MIDI Input Channel (1 to 16, or All) and one Output Channel, set under Utility > MIDI.

Mind CC 24
The FX1 block is CC 22, 23 and 25. CC 24 between them is VCF Env Amt, so a guess that the block is contiguous moves the filter envelope.

Left out
Osc Type, filter type and FX Type have no CC. The selectors that define the sound cannot be changed from here.

General	1
Glide	5

MIDI	1
Mod Wheel	1

Pedals	1
Sustain switch	64

OSC 1	5
Tune	70
Wave	14
Timbre	15
Shape	16
Volume	17

OSC 2	5
Tune	73
Wave	18
Timbre	19
Shape	20
Volume	21

Analog Filter	4
Cutoff	74
Resonance	71
VCF Env Amt	24
Velo Env Mod	94

Cycling Env	5
Rise Shape	68
Rise	76
Fall	77
Hold	78
Fall Shape	69

Envelope	4
Attack	80
Decay	81
Sustain	82
Release	83

LFO 1	1
Rate	85

LFO 2	1
Rate	87

FX1	3
Time	22
Intensity	23
Amount	25

FX2	3
Time	26
Intensity	27
Amount	28

FX3	3
Time	29
Intensity	30
Amount	31

Sequencer	2
Gate	115
Spice	116

Macros	2
M1	117
M2	118

These controls as knobs on your iPhone or iPad
Sequentia has this chart built in, with a looper for knob movement and tempo-locked LFOs on any CC.

synthycraft.com/l/sequentia