Synth

Roland JD-08

84 parameters · 11 sections · plain CC, no NRPN · transcribed from the maker's manual

What it is

The JD-800 as a module, and the largest published map in Roland's Boutique line.

Tone Palette

Tone Palette A to D, on CC 68 to 71, are the machine's own macro sliders. The names are kept as Roland prints them, including its own spelling.

Tone	4
Tone Palette A	68
Tone Palette B	69
Tone Palette C	70
Tone Palette D	71

Pitch	7
Waveform (tx: Encoder) (rx: 0-108)	72
Pitch Coarse	79
Pitch Fine	80
Pitch Random	81
Pitch Key Follow	82
WG LFO1 Depth	83
WG LFO2 Depth	85

Filter	7
TVF Cutoff	3
TVF Resonanse	9
TVF Filter Mode	86
TVF Envelope Depth	87
TVF Key Follow	89
TVF LFO Select	90
TVF LFO Depth	102

Amp	6
TVA Level	103
TVA Bias Point	104
TVA Bias Level	105
TVA Bias Direction	106
TVA LFO Select	107
TVA LFO Depth	108

Pitch envelope	7
Pitch Envelope Time Key Follow	26
Pitch Envelope L0	27
Pitch Envelope T1	28
Pitch Envelope L1	29
Pitch Envelope T2	30
Pitch Envelope T3	31
Pitch Envelope L2	35

Filter envelope	9
Filter Envelope Time Key Follow	46
Filter Envelope T1	47
Filter Envelope L1	48
Filter Envelope T2	50
Filter Envelope L2	51
Filter Envelope T3	52
Filter Envelope Sustain Level	53
Filter Envelope T4	54
Filter Envelope L4	56

Amp envelope	8
Amp Envelope Time Key Follow	55
Amp Envelope T1	57
Amp Envelope L1	58
Amp Envelope T2	59
Amp Envelope L2	60
Amp Envelope T3	61
Amp Envelope Sustain Level	62
Amp Envelope T4	63

LFO	14	
LFO1 Rate		14
LFO1 Delay		15
LFO1 Fade		16
LFO1 Offset		17
LFO1 Key Trg	switch	18
LFO1 Waveform		19
LFO2 Rate		20
LFO2 Delay		21
LFO2 Fade		22
LFO2 Waveform		23
LFO2 Offset		24
LFO2 Key Trg	switch	25
LFO1 Rate (Rate sync)		96
LFO2 Rate (Rate sync)		97

FX	7
FX B Level	12
FX B Reverb Time	13
FX B Reverb Level	91
FX B Delay L Level	92
FX B Chorus Level	93
FX B Delay C Level	94
FX B Delay R Level	95

Voice	8	
Portamento Time		5
Layer		111
Active	switch	112
Solo	switch	115
Legato	switch	116
Portamento		117
Portamento Mode		118
Unison		119

Play	7	
Part Level		7
Expression		11
Bender Range Up		41
Bender Range Down		49
Hold Pedal	switch	64
Sostenuto Pedal	switch	66
Level		110

These controls as knobs on your iPhone or iPad

Sequentia has this chart built in, with a looper for knob movement and tempo-locked LFOs on any CC.

synthycraft.com/l/sequentia