Synth

Roland JX-08

48 parameters · 7 sections · plain CC, no NRPN · transcribed from the maker's manual

What it is

The JX-8P as a module.

Which chart to read

Roland prints two charts for this machine. The system chart marks control change as absent, which is true of the box and false of the sound. These numbers come from the part chart.

Oscillator	15
DCO-1 Level	16
DCO-2 Level	17
DCO-1 Range	20
DCO-1 Enev Mod	21
DCO-2 LFO	25
DCO-1 LFO	26
DCO-1 Waveform	46
DCO-1 Range	47
DCO-2 Fine Tune	56
DCO Cross Mod	59
DCO Envelope Mode	60
DCO-2 Waveform	61
DCO-2 Range	62
DCO-2 ENV	63
DCO-2 Coarse 1OCT	87

Filter	6
VCF Cutoff	3
VCF Resonance	9
VCF LFO Depth	28
VCF ENV	81
VCF Key Follow	82
VCF Envelope Mode	84

Envelope	13
Mixer ENV	18
Mixer Envelope Mode	19
ENV1 Decay	80
ENVELOPE1 Attack	83
ENVELOPE1 Sustain	85
ENVELOPE1 Release	86
ENVELOPE2 Attack	89
ENVELOPE2 Decay	90
ENVELOPE2 Sustain	102
ENVELOPE2 Release	103
ENVELOPE1 Key Follow	104
ENVELOPE2 Key Follow	105
Amp Envelope Mode	109

LFO	3
LFO Delay Time	27
LFO Rate	29
LFO Waveform	35

Amp	1
Amp Level	110

Voice	4
Portamento Time	5
Portamento Time	117
Portamento SW switch	118
Solo/poly/unison switch	119

Play	6
Pattern Part Level	7
Expression	11
Bend Pitch	41
Hold Pedal switch	64
Filter HPF	79
Reverb Send Level	91

These controls as knobs on your iPhone or iPad

Sequentia has this chart built in, with a looper for knob movement and tempo-locked LFOs on any CC.

synthycraft.com/l/sequentia