Synth

Sequential Pro 3

103 parameters · 10 sections · plain CC, no NRPN · transcribed from the maker's manual

Before you send

In Global, set the MIDI parameter receive setting to CC. This is one of the biggest maps Sequential publishes.

Names as printed

The names are kept as Sequential prints them, which is why a few rows repeat a name. The number next to each one is what matters.

Oscillators	30
Audio In Level	8
Audio In Gain	9
Osc. 1 Glide Rate	54
Osc. 2 Glide Rate	55
Osc. 3 Glide Rate	56
Oscillator Glide	65
Osc. 1 Octave	66
Osc. 1 Fine	67
Osc. 1 Level	68
Osc. 1 Shape	69
Osc. 1 Shape Mod	70
Osc. 1 Sync On/Off switch	71
Osc. 1 Slop	72
Noise level	73
Osc. 2 Octave	75
Osc. 2 Fine	76
Osc. 2 Level	77
Osc. 2 Shape	78
Osc. 2 Shape Mod	79
Osc. 2 Sync On/Off switch	80
Osc. 2 Slop	81
Osc. 3 Octave	82
Osc. 3 Fine	83
Osc. 3 Level	84
Osc. 3 Shape	85
Osc. 3 Shape Mod	86
Osc. 3 LFO Mode	87
Osc. 3 Slop	88
Feedback Amount	89
Feedback Tuning	90

Filter	16
Filter Cutoff	33
Filter Resonance	34
Filter Keyboard	35
Filter Drive	36
Filter Type	37
Filter Env. Amount	47
Filter Env. Velocity	48
Filter Env. Delay	49
Filter Env. Attack	50
Filter Env. Decay	51
Filter Env. Sustain	52
Filter Env. Release Frequency	53
Brightness	74
Ladder Res Comp	102
State Variable Filter	103
State Variable Filter	104

Envelopes	9
VCA Env. Amount	40
VCA Env. Velocity	41
VCA Env. Delay	42
VCA Env. Attack	43
VCA Env. Decay	44
VCA Env. Sustain	45
VCA Env. Release Frequency	46
Ext. In Env. Follower	93
Ext. In Env. Follower	94

LFO 1	4
LFO 1 Freq	105
LFO 1 Amount	106
LFO 1 Shape	107
LFO 1 Sync On/Off switch	108

LFO 2	4
LFO 2 Frequency	109
LFO 2 Amount	110
LFO 2 Shape	111
LFO 2 Sync On/Off switch	112

LFO 3	4
LFO 3 Frequency	113
LFO 3 Amount	114
LFO 3 Shape	115
LFO 3 Sync On/Off switch	116

Effects	17
FX 1 On/Off switch	16
FX 1 Type	17
FX 1 Mix On/Off switch	18
FX 1 Param 1	19
FX 1 Param 2	20
FX 1 Param 3	21
FX 1 Sync On/Off switch	22
FX 1 Sync Rate	23
FX2 On/Off switch	24
FX 2 Select	25
FX 2 Mix	26
FX 2 Param 1	27
FX 2 Param 2	28
FX 2 Param 3	29
FX 2 Sync On/Off switch	30
FX 2 Sync Rate	31
Distortion Amount	91

Sequencer	7
BPM	3
Arp. On/Off On/Off switch	58
Arp. Mode	59
Arp. Range	60
Arp. Relatch On/Off switch	61
Clock Divide	62
Arp. Repeats	63

Voice	2
Glide Mode (Portamento Time)	5
Voice Volume	12

Play	10
Mod Wheel	1
Breath Controller	2
Foot Controller	4
MIDI Volume	7
Expression	11
Paraphonic On/Off switch	13
Slider 1 Position	14
Swing	57
Grunge On/Off switch	92
Ext. In Gain	95

These controls as knobs on your iPhone or iPad
Sequentia has this chart built in, with a looper for knob movement and tempo-locked LFOs on any CC.

synthycraft.com/l/sequentia