Synth

Sonicware LIVEN XFM

40 parameters · 6 sections · plain CC, no NRPN · transcribed from the maker's manual

Two kinds of channel

The chart prints them as PT.CH and T1.CH to T4.CH. Pattern controls answer on the pattern channel. Everything else answers on the channel of the track you are aiming at, so four tracks take four channels.

Numbered parameters

Synth Parameter 1 to 8 are CC 29 to 36.

Pattern	7
Velocity	5
FX Type	20
FX Speed	21
FX Amount	22
Ptn Level	23
Seq Mode	24
Line In to FX	25

Synth	10
Synth	27
Octave	28
Synth Parameter 1	29
Synth Parameter 2	30
Synth Parameter 3	31
Synth Parameter 4	32
Synth Parameter 5	33
Synth Parameter 6	34
Synth Parameter 7	35
Synth Parameter 8	36

Filter	5
Filter	37
Fltr Cutoff	38
Fltr Reso	39
Fltr Env Depth	40
Fltr Env Time	41

LFO	5
LFO Shape	42
LFO Delay	43
LFO Rate	44
LFO Pitch	45
LFO Filter Depth	46

Sweep	4
Sweep	51
Sweep Speed	52
Sweep Range	53
Sweep Curve	54

Track	9
Release & Gate	47
Dice	48
Swing	49
To FX	50
Voice Mode	55
Voice Adj	56
Transpose	57
Rnd Step	58
Prm Lock	59

These controls as knobs on your iPhone or iPad

Sequentia has this chart built in, with a looper for knob movement and tempo-locked LFOs on any CC.

synthycraft.com/l/sequentia