Synth

ASM Hydrasynth

114 parameters · 29 sections · plain CC, no NRPN · transcribed from the maker's manual

One map for the family

The same chart serves the Explorer, Desktop, Keyboard and Deluxe.

Fives and eights

Five envelopes, five LFOs and eight macros, all on numbers. That is why this is one of the largest charts on the site. The eight macros are CC 16 to 23, which makes them the quickest thing to put under a controller.

OSC 1	2
OSC1 wavscan	24
OSC 1 Cent	111

OSC 2	2
OSC2 WavScan	26
OSC 2 Cent	112

OSC 3	1
OSC 3 Cent	113

Mixer	16
Noise Vol	3
Noise Pan	8
Ring Mod Vol	9
Ring Mod Pan	10
RM12 Depth	43
OSC1 Vol	44
OSC1 Pan	45
OSC2 Vol	46
OSC2 Pan	47
OSC3 Vol	48
OSC3 Pan	49
OSC 3 FRate	114
Noise FRate	115
Ring Mod FRate	116
OSC1 FRate	118
OSC2 FRate	119

Mutator 1	3
Mutator1 Ratio	29
Mutator1 Depth	30
Mutator1 Dry/Wet	31

Mutator 2	3
Mutator2 Ratio	33
Mutator2 Depth	34
Mutator2 Dry/Wet	35

Mutator 3	3
Mutator3 Ratio	36
Mutator3 Depth	37
Mutator3 Dry/Wet	39

Mutator 4	3
Mutator4 Ratio	40
Mutator4 Depth	41
Mutator4 Dry/Wet	42

Filter 1	7
Filter 1 Drive	50
Filter 1 Keytrack	51
Filter 1 LFO1amt	52
Filter 1 Vel Env	53
Filter 1 ENV1amt	54
Filter 1 Res	71
Filter 1 Cutoff	74

Filter 2	7
Filter 2 Cutoff	55
Filter 2 Res	56
Filter 2 Type	57
Filter 2 Keytrack	58
Filter 2 LFO1amt	59
Filter 2 Vel Env	60
Filter 2 ENV1amt	61

Amp	1
Amp LFO2amt	62

ENV 1	4
ENV1 Attack	81
ENV1 Decay	82
ENV1 Sustain	83
ENV1 Release	84

ENV 2	4
ENV2 Attack	85
ENV2 Decay	86
ENV2 Sustain	87
ENV2 Release	88

ENV 3	4
ENV3 Attack	89
ENV3 Decay	90
ENV3 Sustain	96
ENV3 Release	97

ENV 4	4
ENV4 Attack	25
ENV4 Decay	27
ENV4 Release	124
ENV4 Sustain	125

ENV 5	4
ENV5 Attack	102
ENV5 Decay	103
ENV5 Sustain	104
ENV5 Release	105

LFO 1	2
LFO1 Gain	70
LFO1 Rate	72

LFO 2	2
LFO2 Gain	28
LFO2 Rate	73

LFO 3	2
LFO3 Gain	75
LFO3 Rate	76

LFO 4	2
LFO4 Gain	77
LFO4 Rate	78

LFO 5	2
LFO5 Gain	79
LFO5 Rate	80

Macros	8
Macro 1	16
Macro 2	17
Macro 3	18
Macro 4	19
Macro 5	20
Macro 6	21
Macro 7	22
Macro 8	23

ARP	7
ARP Division	106
ARP Gate	107
ARP Mode	108
ARP Ratchet	109
ARP Chance	110
ARP Octave	120
ARP Length	122

Delay	4
Delay Feedback	14
Delay Time	15
Delay Wet tone	63
Delay Dry/Wet	92

Reverb	3
Reverb Time	65
Reverb Tone	67
Reverb Dry/Wet	91

Voice	4
GlidTime	5
Glide	66
Detune	95
StWidth	117

Post-fx	3
POST-FX Param1	68
POST-FX Param2	69
POST FX Mix	94

Pre-fx	3
PRE-FX Param1	12
PRE-FX Param2	13
PRE-FX Mix	93

System	4
Modulation wheel.	1
Master Volume	7
Expression pedal switch	11
Sustain pedal switch	64

These controls as knobs on your iPhone or iPad
Sequentia has this chart built in, with a looper for knob movement and tempo-locked LFOs on any CC.

synthycraft.com/l/sequentia