Synth

Behringer JT-4000M MICRO

31 parameters · 7 sections · plain CC, no NRPN · transcribed from the maker's manual

Channels

Separate transmit and receive channels in the settings menu.

Five more controls

The M model is a different machine from the JT-4000, not a color variant. It answers Balance on CC 29, Env Amount on CC 47, LFO 1 Wave on CC 54, LFO 2 Wave on CC 55 and LFO 1 Dest on CC 56.

Oscillator	9
OSC 1 Wave	24
OSC 2 Wave	25
Balance	29
OSC 1 Coarse	115
OSC 2 Coarse	116
OSC 1 Fine	111
OSC 2 Fine	112
OSC 1 PWM	113
OSC 2 PWM	114

Filter	3
Cutoff	74
Resonance	71
Env Amount	47

Filter envelope	4
Attack	85
Decay	86
Sustain	87
Release	88

Amp envelope	4
Attack	81
Decay	82
Sustain	83
Release	84

LFO	7
LFO 1 Rate	72
LFO 1 Amount	70
LFO 1 Wave	54
LFO 1 Dest	56
LFO 2 Rate	73
LFO 2 Amount	28
LFO 2 Wave	55

Ring mod	2	
Amount		95
On	switch	96

Play	2
Modulation	1
Porta Time	5

These controls as knobs on your iPhone or iPad
Sequentia has this chart built in, with a looper for knob movement and tempo-locked LFOs on any CC.
synthycraft.com/l/sequentia