Effect

Elektron Analog Heat MKII

42 parameters · 8 sections · plain CC, no NRPN · transcribed from the maker's manual

Channels

Everything listens on the single MIDI channel set under SETTINGS > MIDI > CHANNELS. The Heat MKII has no separate FX or performance channel.

Control inputs

The Control In group sets where the CV and expression inputs go and how deep: a destination and a depth for CV A, Exp A, CV B and Exp B, on CC 85 to 92.

Amp & Circuit	5
Circuit	70
Drive	12
Wet Level	11
Dry/Wet	8
Volume	7

Filter & EQ 1	5
VCF Mode	80
Freq	74
Reso	71
Env>Filter	14
LFO>Filter	15

Filter & EQ 2	4
Freq Pan	79
Dirt	13
EQ Low	9
EQ High	10

Envelope 1	4
Env Mode	19
Attack	73
Release	72
Threshold	16

Envelope 2	6
Base	17
Width	18
Dest 1	75
Depth 1	20
Dest 2	76
Depth 2	21

LFO 1	4
Speed	22
Mult	23
Wave	83
Start	26

LFO 2	6
Fade	24
Mode	25
Dest 1	77
Depth 1	27
Dest 2	78
Depth 2	28

Control In	8
CV A Dest	85
CV A Depth	86
Exp A Dest	87
Exp A Dpth	88
CV B Dest	89
CV B Depth	90
Exp B Dest	91
Exp B Dpth	92

These controls as knobs on your iPhone or iPad

Sequentia has this chart built in, with a looper for knob movement and tempo-locked LFOs on any CC.

synthycraft.com/l/sequentia