Synth

Elektron Monomachine

63 parameters · 9 sections · plain CC, no NRPN · transcribed from the maker's manual

Channels

Each track listens on its own channel, from the base channel to base plus 5, and all six use the same CC map. The Multi Trig mod wheel macros listen on the separate Multi Trig channel.

Machine parameters

Synth 1 to Synth 8 are CC 48 to 55 and follow the machine on the track. The filter is a pair, Base on CC 72 and Width on CC 73, not a single cutoff.

Track		5
Joy Up		1
Joy Down		2
Mute	switch	3
Level		7
Pan		10

Synthesis	8
Synth 1	48
Synth 2	49
Synth 3	50
Synth 4	51
Synth 5	52
Synth 6	53
Synth 7	54
Synth 8	55

Amp	8
Attack	56
Hold	57
Decay	58
Release	59
Dist	60
Vol	61
Amp Pan	62
Portamento	63

Filter	8
Base	72
Width	73
HPQ	74
LPQ	75
Attack	76
Decay	77
Base Ofs	78
Width Ofs	79

Effects	8
EQ Freq	80
EQ Gain	81
SRR	82
Dly Time	83
Dly Send	84
Dly Fdbk	85
Dly Filt B	86
Dly Filt W	87

LFO 1	8
Page	88
Dest	89
Trig	90
Wave	91
Mult	92
Speed	93
Interlace	94
Depth	95

LFO 2	8
Page	104
Dest	105
Trig	106
Wave	107
Mult	108
Speed	109
Interlace	110
Depth	111

LFO 3	8
Page	112
Dest	113
Trig	114
Wave	115
Mult	116
Speed	117
Interlace	118
Depth	119

Multi Trig PERF ch	2
ModWhl Up	1
ModWhl Dn	2

These controls as knobs on your iPhone or iPad
Sequentia has this chart built in, with a looper for knob movement and tempo-locked LFOs on any CC.
synthycraft.com/l/sequentia