Groovebox

Korg volca sample 2

19 parameters · 5 sections · plain CC, no NRPN · transcribed from the maker's manual

Channels

The ten parts answer on channels 1 to 10, one part per channel. This is the factory layout. Reverb Mix on CC 91 is the exception. It is global and listens on channel 1 only.

Before you send

If nothing responds, check that MIDI RX ShortMessage is On. The single channel layout is a different map and is not this one. The switches follow Korg's own threshold: 64 and up is on.

Sample · per part	6
Sample MSB	3
Sample LSB	35
Start	40
Length	41
Speed	43
Speed Chrom	49

Shape · per part	6
Hi Cut	42
Amp Attack	47
Amp Decay	48
Pitch Int	44
Pitch Attack	45
Pitch Decay	46

Mix · per part	3
Level	7
Pan	10
Trig Delay	50

Switches · per part	3	
Loop	switch	68
Reverb	switch	70
Reverse	switch	75

Global · ch 1	1
Reverb Mix	91

These controls as knobs on your iPhone or iPad

Sequentia has this chart built in, with a looper for knob movement and tempo-locked LFOs on any CC.

synthycraft.com/l/sequentia