Synth

Korg wavestate

48 parameters · 6 sections · plain CC, no NRPN · transcribed from the maker's manual

What these knobs do

These are the Mod Knobs, and each program decides what its own knobs do. The same number moves a different parameter in a different sound. The numbers are Korg's factory assignments for the knobs. The engine itself is not reachable by CC on this machine.

Channels

Layers can listen on the global channel or on a channel of their own. One document covers the wavestate, mk II, SE and module.

Performance	8
Knob 1	24
Knob 2	25
Knob 3	26
Knob 4	27
Knob 5	28
Knob 6	29
Knob 7	30
Knob 8	31

Layer B	8
Knob 1	88
Knob 2	89
Knob 3	90
Knob 4	91
Knob 5	92
Knob 6	93
Knob 7	94
Knob 8	95

Layer D	8
Knob 1	110
Knob 2	111
Knob 3	112
Knob 4	113
Knob 5	114
Knob 6	115
Knob 7	116
Knob 8	117

Layer A	8
Knob 1	80
Knob 2	81
Knob 3	82
Knob 4	83
Knob 5	84
Knob 6	85
Knob 7	86
Knob 8	87

Layer C	8
Knob 1	102
Knob 2	103
Knob 3	104
Knob 4	105
Knob 5	106
Knob 6	107
Knob 7	108
Knob 8	109

Play	8
Vector X	16
Vector Y	17
Scale Select	9
Modulation	1
Volume	7
Pan	10
Expression	11
Damper switch	64

These controls as knobs on your iPhone or iPad
Sequentia has this chart built in, with a looper for knob movement and tempo-locked LFOs on any CC.
synthycraft.com/l/sequentia