Synth

# Moog Subsequent 37

73 parameters · 15 sections · plain CC, no NRPN · transcribed from the maker's manual

**Channels**
One MIDI channel for everything: IN 1 to 16 or ALL, OUT 1 to 16, default 1. DUO MODE is two note paraphonic on that same channel, not a second channel.

**Switches send 64**
Every switch in this chart sends 64 for on, because that is the value the manual prints.

**Left out**
The arpeggiator settings, the mod depths and the envelope loop live on NRPN only, so they are not reachable from here.

| Osc 1 | 2 |
|---|---|
| Wave | 9 |
| Octave | 74 |

| Osc 2 | 6 |
|---|---|
| Wave | 14 |
| Octave | 75 |
| Freq | 12 |
| Beat Freq | 13 |
| Hard Sync switch · on 64 | 77 |
| KB Ctrl | 111 |

| Oscillators | 2 |
|---|---|
| KB Reset switch · on 64 | 81 |
| Duo Mode switch · on 64 | 110 |

| Mixer | 5 |
|---|---|
| Osc 1 Level | 114 |
| Sub Level | 115 |
| Osc 2 Level | 116 |
| Noise Level | 117 |
| Fdbk/Ext Lvl | 118 |

| Filter | 6 |
|---|---|
| Cutoff | 19 |
| Resonance | 21 |
| Multidrive | 18 |
| KB Amt | 22 |
| EG Amt | 27 |
| Slopes | 109 |

| Filter EG | 10 |
|---|---|
| Attack | 23 |
| Decay | 24 |
| Sustain | 25 |
| Release | 26 |
| Delay | 103 |
| Hold | 105 |
| KB Amt | 79 |
| Vel Amt | 86 |
| Reset switch · on 64 | 82 |
| Multi Trig switch · on 64 | 112 |

| Amp EG | 10 |
|---|---|
| Attack | 28 |
| Decay | 29 |
| Sustain | 30 |
| Release | 31 |
| Delay | 104 |
| Hold | 106 |
| KB Amt | 80 |
| Vel Amt | 87 |
| Reset switch · on 64 | 83 |
| Multi Trig switch · on 64 | 113 |

| LFO 1 | 3 |
|---|---|
| Rate | 3 |
| Range | 76 |
| KB Reset switch · on 64 | 93 |

| LFO 2 | 3 |
|---|---|
| Rate | 8 |
| Range | 78 |
| KB Reset switch · on 64 | 95 |

| Mod 1 | 6 |
|---|---|
| Source | 71 |
| Dest | 91 |
| Pitch Amt | 4 |
| Filter Amt | 11 |
| PGM Dst Amt | 20 |
| Osc 1/2 Sel | 70 |

| Mod 2 | 6 |
|---|---|
| Source | 72 |
| Dest | 92 |
| Pitch Amt | 15 |
| Filter Amt | 16 |
| PGM Dst Amt | 17 |
| Osc 1/2 Sel | 88 |

| Glide | 5 |
|---|---|
| Glide On switch · on 64 | 65 |
| Time | 5 |
| Type | 85 |
| Legato switch · on 64 | 94 |
| Dest Osc | 102 |

| Arp | 2 |
|---|---|
| Arp On switch · on 64 | 73 |
| Latch switch · on 64 | 69 |

| Keyboard | 6 |
|---|---|
| Octave | 89 |
| Transpose | 119 |
| Bend Up | 107 |
| Bend Down | 108 |
| Mod Wheel | 1 |
| Hold Pedal switch · on 64 | 64 |

| Output | 1 |
|---|---|
| Master Vol | 7 |

These controls as knobs on your iPhone or iPad

Sequentia has this chart built in, with a looper for knob movement and tempo-locked LFOs on any CC.

synthycraft.com/l/sequentia