Synth

Sequential Prophet-5 / Prophet-10

59 parameters · 9 sections · plain CC, no NRPN · transcribed from the maker's manual

Before you send

In Global, set the MIDI parameter receive setting to CC. One map serves both the Prophet-5 and the Prophet-10 of the rev4 reissue.

Switches and Vintage

The switch rows answer 1 for on. Filter Rev Select on CC 41 and Vintage on CC 85 belong to the reissue: they choose which revision of the original the machine behaves as.

Oscillator A 5

OSC A Frequency		3
OSC A Saw ON/FF	switch · on 1	15
OSC A Square ON/OFF	switch · on 1	20
OSC A Pulse Width		21
OSC A Level		27

Oscillator B 9

OSC B Frequency		9
OSC B Fine Tune		14
OSC B Pulse Width		22
OSC B Low Freq ON/OFF	switch · on 1	24
OSC B Keyboard ON/OFF	switch · on 1	25
OSC B Level		28
OSC B Saw ON/OFF	switch · on 1	30
OSC B Tri ON/OFF	switch · on 1	52
OSC B Square ON/OFF	switch · on 1	116

Mixer 1

Noise Level		29

Filter 14

Resonance		31
Filter Keyboard Track OFF/HALF/FULL		35
Filter Rev Select	switch · on 1	41
LFO Filter ON/OFF	switch · on 1	58
Poly Mod Filter ON/OFF	switch · on 1	63
Cutoff		73
Brightness		74
Pressure Filter	switch · on 1	86
Envelope Filter Amount		89
Envelope Filter Velocity ON/OFF	switch · on 1	90
Attack Filter		103
Decay Filter		105
Sustain Filter		107
Release Filter		109

Envelopes 7

Poly Mod Filt ENV Amount		59
Envelope VCA Velocity ON/OFF	switch · on 1	102
Attack VCA		104
Decay VCA		106
Sustain VCA		108
Release VCA		110
Release ON/OFF	switch · on 1	111

LFO 10

LFO Frequency		46
LFO Initial Amount		47
LFO Source Mix		53
LFO Freq A ON/OFF	switch · on 1	54
LFO Freq B ON/OFF	switch · on 1	55
LFO Freq PW A ON/OFF	switch · on 1	56
LFO Freq PW B ON/OFF	switch · on 1	57
LFO Saw ON/OFF	switch · on 1	117
LFO Tri ON/OFF	switch · on 1	118
LFO Square ON/OFF	switch · on 1	119

Poly Mod 3

Poly Mod OSC B Amount		60
Poly Mod Freq A ON/OFF	switch · on 1	61
Poly Mod PW ON/OFF	switch · on 1	62

Voice 8

OSC Sync ON/OFF	switch · on 1	23
Glide Rate		26
Pitch Wheel Range		70
Retrigger And Unison Assign	switch	71
Vintage		85
Unison ON/OFF	switch · on 1	112
Unison Voice Count		113
Unison Detune		114

Play 2

Master Volume		7
Pressure LFO	switch · on 1	87

These controls as knobs on your iPhone or iPad

Sequentia has this chart built in, with a looper for knob movement and tempo-locked LFOs on any CC.

synthycraft.com/l/sequentia