Synth

Sequential Prophet Rev2

64 parameters · 10 sections · plain CC, no NRPN · transcribed from the maker's manual

Before you send

Set Global > MIDI Param Rcv to CC. NRPN is the preferred method on this machine and the default, so a box of knobs needs the other setting. Then match the Rev2's MIDI channel.

Layers

A/B Mode is CC 18 and Split Pt is CC 39, so stacking and splitting the two layers can be automated too.

Osc	11
Osc1 Freq	20
Osc1 Fine	21
Osc1 Shape	22
O1 ShpMod	30
Osc1 Glide	23
Osc2 Freq	24
Osc2 Fine	25
Osc2 Shape	26
O2 ShpMod	31
Osc2 Glide	27
Slop	9

Mixer	8
Osc Mix	28
Sub Osc	8
Noise	29
VCA Level	113
Voice Vol	37
Master Vol	7
Pan Spread	114
Pan Mode	10

Filter	6
Cutoff	102
Resonance	103
Key Amt	104
Audio Mod	105
Env Amt	106
Env Vel	107

Filter Env	5
Delay	108
Attack	109
Decay	110
Sustain	111
Release	112

Amp Env	7
Delay	117
Attack	118
Decay	119
Sustain	75
Release	76
Env Amt	115
Env Vel	116

Env 3	8
Delay	88
Attack	89
Decay	90
Sustain	77
Release	78
Amount	86
Velocity	87
Dest	85

FX	5	
FX On	switch	16
FX Type		3
FX Mix		17
FX Param 1		12
FX Param 2		13

Arp & Seq	7	
Arp On	switch	33
Arp Mode		34
Arp Range		35
Arp Rpts		36
Seq Type		19
BPM		14
Clock Div		15

Perform	5	
Mod Wheel		1
Brightness		74
Sustain Ped	switch	64
Glide On	switch	65
Glide Mode		5

Layer	2
A/B Mode	18
Split Pt	39

These controls as knobs on your iPhone or iPad

Sequentia has this chart built in, with a looper for knob movement and tempo-locked LFOs on any CC.

synthycraft.com/l/sequentia