Synth

Sequential Take 5

83 parameters · 8 sections · plain CC, no NRPN · transcribed from the maker's manual

Before you send
Set Param Rcv to CC on the machine. CC is not its default.

Switches answer 1
Every switch in this chart answers 1 for on, not 127, because that is the range Sequential prints against it.

Oscillators 16

Osc1 Octave		8
Osc1 Fine Freq		9
Osc1 Shape		10
Osc2 Octave		13
Osc2 Fine Freq		14
Osc2 Shape		15
Osc Sync	switch · on 1	39
Osc1 Level		40
Osc2 Level		41
Sub Osc Level		42
Noise Level		43
FM On/Of	switch · on 1	44
Osc1 Glide Rate		65
Osc2 Glide Rate		66
Osc1 Key Tracking On/Off	switch · on 1	87
Osc2 Key Tracking On/Off	switch · on 1	88

Filter 6

Filter Cutoff		33
Filter Resonance		34
Filter Drive		35
Filter Key Tracking		36
Vintage		37
Brightness		74

Envelope 1 7

Env1 Delay		45
Env1 Attack		46
Env1 Decay		47
Env1 Sustain		48
Env1 Release		49
Env1 Amount		50
Env1 Vel. On/Off	switch · on 1	51

Envelope 2 7

Env2 Del		52
Env2 Attack		53
Env2 Decay		54
Env2 Sustain		55
Env2 Release		56
Env2 Amount		57
Env2 Vel. On/Off	switch · on 1	58

LFO 10

LFO1 Freq		75
LFO1 Amount		76
LFO1 Shape		77
LFO1 Sync On/Off	switch · on 1	78
LFO1 Note Reset	switch · on 1	79
LFO2 Freq		80
LFO2 Amount		81
LFO2 Shape		82
LFO2 Sync On/Off	switch · on 1	83
LFO2 Note Reset	switch · on 1	84

Effects 14

FX On/Off	switch · on 1	16
FX Type		17
FX Depth/Mix		18
FX Time		19
FX Feedback/Misc		20
FX Clock Sync On/Off	switch · on 1	21
FX Clock Sync Rate		22
Reverb On/Off	switch · on 1	23
Reverb Wet/Dry Mix		24
Reverb Size		25
Reverb Predelay		26
Reverb Decay		27
Reverb Tone		28
Distortion		67

Voice 17

Glide Mode		5
Voice Volume		12
Unison On/Off	switch · on 1	31
Arp On/Off	switch · on 1	59
Arp Mode		60
Arp Octave		61
Arp Repeats		62
Clock Divide		63
Glide On/Off	switch · on 1	68
Env Routing		69
Unison Voice Count		70
Unison Detune		71
Unison Key Mode		72
Unison Retrigger	switch · on 1	73
Pitch Bend Range Up		85
Pitch Bend Range Down		86
Key Split Note		89

Play 6

Mod Wheel		1
Breath		2
BPM		3
Foot Controller		4
Master Volume		7
Expression Pedal		11

These controls as knobs on your iPhone or iPad
Sequentia has this chart built in, with a looper for knob movement and tempo-locked LFOs on any CC.

synthycraft.com/l/sequentia