Effect

Strymon BigSky

54 parameters · 13 sections · plain CC, no NRPN · transcribed from the maker's manual

A block per machine

The twelve reverb machines each own a block of numbers. A control in a machine's block only does something when that machine is the one loaded.

Small ranges

Strymon prints a range against every row, and most are small: 0 to 20 or 0 to 2, not 0 to 127. Sweep a full knob and most of its travel does nothing.

Machine	14	
Tone		3
Param 1		9
Mod		14
Mix		15
Param 2		16
Decay		17
Pre-Delay		18
Type encoder		19
Value encoder	switch · on 1	20
Persist Off/On	switch · on 1	22
Boost		23
Expression Off/On	switch · on 1	60
Freeze/Infinite	switch · on 1	70
MIDI Clock Off/On	switch · on 1	71

Bloom	3	
Feedback		30
Low End		31
Length		32

Chorale	2	
Vowel		33
Reso		34

Cloud	2	
Diffusion		37
Low End		38

Hall	3	
Low End		39
Size	switch · on 1	40
Mid		42

Magneto	4	
Spacing	switch · on 1	54
Low End		55
Diffusion		56
Heads		57

Nonlinear	6	
Mod Speed		43
Low End		44
Diffusion		45
Shape		46
Late Decay		47
Late Level		48

Plate	2	
Size	switch · on 1	68
Low End		69

Reflections	4	
Loc X		49
Loc Y		50
Shape		51
Low End		52

Room	3	
Diffusion		58
Size	switch · on 1	59
Low End		61

Shimmer	5	
Low End		24
Shift 1		25
Shift 2		26
Amount		27
Mode		28

Spring	3	
# Springs		62
Dwell		63
Low End		64

Swell	3	
Low End		65
Rise		66
Mode	switch · on 1	67

These controls as knobs on your iPhone or iPad
Sequentia has this chart built in, with a looper for knob movement and tempo-locked LFOs on any CC.
synthycraft.com/l/sequentia