Synth

Waldorf Rocket

21 parameters · 6 sections · plain CC, no NRPN · transcribed from the maker's manual

Standard assignment

The manual prints two columns: the standard assignment and an alternative you switch to by SysEx. This chart is the standard one. Headphone volume, Filter Type, Boost and Launch send nothing. The manual says so.

A short envelope

The envelope is Decay, Sustain and Release with no Attack, and Sustain and Release are switches. That is how the Rocket is built, not a gap in the chart.

OSC	4
Wave	70
Tune	79
Shape	31
Glide	5

Filter	4
Cutoff	74
Resonance	71
Env Mod	73
Keytrack	83

Envelope	3
Decay	75
Sustain switch · on 1	103
Release switch · on 1	72

LFO	5
Speed	76
Depth	77
Shape	78
Target	18
Vibrato	80

Arp	3
Tempo	14
Range	12
Direction	13

Mix	2
Mod wheel	1
Sustain pedal switch · on 64	64

These controls as knobs on your iPhone or iPad

Sequentia has this chart built in, with a looper for knob movement and tempo-locked LFOs on any CC.

synthycraft.com/l/sequentia